

TECHNICAL DATA SHEET FOR: 1000kVA Silenced Generator

John F Hunt
POWER

- HOT DIP GALVANISED SOUND ATTENUATED ENCLOSURE.
- BUNDED 1900 LITRE BASE FUEL TANK COMPLETE WITH 3 WAY VALVE
- 4 BASE LIFT POINTS
- 4 POLE CIRCUIT BREAKER WITH EARTH LEAKAGE PROTECTION WITH ON OFF SWITCH
- DEEP SEA 7510 LOAD SHARE CONTROL PANEL
- PLASTIC COATED LOCKS AND HANDLES. LOCKABLE CANOPY WITH COMMON SINGLE KEY
- RACOR FILTER
- 50/60 Hz SWITCHABLE
- LOW WATER LEVEL ALARM
- LOW OIL LEVEL ALARM



- CUMMINS WATER SEPARATOR FILTER
- SUMP OIL VAC PUMP
- BATTERY ISOLATOR
- LOW OIL PRESSURE SENSOR
- WATER TEMPERATURE SENSOR
- CT FOR GENSET PARALLELING
- HARDWIRE VIA COPPER BUSBAR
- MICROSWITCH PROTECTION
- MOTORIZED MCCB
- ALTERNATOR ANTI CONDENSATION HEATER
- R731 3 PHASE REGULATOR
- BATTERY CHARGER

ENGINE Ref:- CUMMINS ALTERNATOR Ref:- LEROY SOMER

Standby kVA	Prime Power kVA.	Engine Make / Type	Governor	Tank Capacity (litres)	Fuel consumption (L/H)			dB(A) @ 7 m	Size	Weight (kg)	Control Panel
					50%	75%	100%				
1120	1017	COMMINS	Electronic	1900	102	151	202	70	20' High Cube Container	12500	Deep Sea 7510 Loadshare

South East Depot – Europa Park, London Road
Grays, Essex, RM20 4DB
T: 01375 366766 E:power@johnfhunt.co.uk

Midlands Depot – Fairfield Park, Off Fairfield Road,
Halesowen, West Midlands B62 9JL
T: 0121 559 1818 E:power@johnfhunt.co.uk

South West Depot – Bradley Road,
Bristol BS20 7NZ
T: 0117 901 2199 E:power@johnfhunt.co.uk

North East Depot – Station Lane, Birtley, Gateshead,
Tyne & Wear DH2 1AJ
T: 0191 4111 200 E:power@johnfhunt.co.uk

www.johnfhuntpower.co.uk