

# TECHNICAL DATA SHEET FOR: 1250kVA Silenced Generator



- HOT DIP GALVANISED SOUND ATTENUATED ENCLOSURE.
- BUNDED 1900 LITRE BASE FUEL TANK COMPLETE WITH 3 WAY VALVE
- 4 BASE LIFT POINTS
- 4 POLE CIRCUIT BREAKER WITH EARTH LEAKAGE PROTECTION WITH ON OFF SWITCH
- DEEP SEA 8610 LOAD SHARE CONTROL PANEL
- PLASTIC COATED LOCKS AND HANDLES. LOCKABLE CANOPY WITH COMMON SINGLE KEY
- RACOR FILTER
- 50/60 Hz SWITCHABLE
- LOW WATER LEVEL ALARM
- LOW OIL LEVEL ALARM



- CUMMINS WATER SEPARATOR FILTER
- SUMP OIL VAC PUMP
- BATTERY ISOLATOR
- LOW OIL PRESSURE SENSOR
- WATER TEMPERATURE SENSOR
- CT FOR GENSET PARALLELING
- HARDWIRE VIA COPPER BUSBAR
- MICROSWITCH PROTECTION
- MOTORIZED MCCB
- ALTERNATOR ANTI CONDENSATION HEATER
- BATTERY CHARGER
- R731 3 PHASE REGULATOR

ENGINE Ref:- CUMMINS ALTERNATOR Ref:- LEROY SOMER / MECC ALTE

Standby kVA	Prime Power kVA.	Engine Make / Type	Governor	Tank Capacity (litres)	Fuel Consumption (L/H)			dB(A) @ 7 m	Size	Weight (kg)	Control Panel
					50%	75%	100%				
1375	1250	CUMMINS	Electronic	1900	112	172	234	62	20' High Cube Container	19500	Deep Sea 8610 Loadshare

**South East Depot** – Europa Park, London Road  
Grays, Essex, RM20 4DB.  
T: 01375 366766 E:power@johnfhunt.co.uk

**Midlands Depot** – Fairfield Park, Off Fairfield Road,  
Halesowen, West Midlands. B62 9JL  
T: 0121 559 1818 E:power@johnfhunt.co.uk

**South West Depot** – Bradley Road,  
Bristol BS20 7NZ  
T: 0117 901 2199 E:power@johnfhunt.co.uk

**North East Depot** – Station Lane, Birtley, Gateshead,  
Tyne & Wear DH2 1AJ.  
T: 0191 4111 200 E:power@johnfhunt.co.uk

[www.johnfhuntpower.co.uk](http://www.johnfhuntpower.co.uk)