

TECHNICAL DATA SHEET FOR: 800kVA Silenced Generator



- HOT DIP GALVANISED SOUND ATTENUATED ENCLOSURE
- AVERAGE 70 dB(A) @ 7 METRES.
- POWDER COATED GREY RAAL 7035
- FORKLIFT POCKETS COMPLETE WITH RUBBER BUMPERS
- 4 POLE CIRCUIT BREAKER WITH VARIABLE EARTH LEAKAGE PROTECTION AND ON/OFF SWITCH.
- DEEP SEA 8610 LOADSHARE SYNCH CONTROL PANEL
- BATTERY ISOLATOR
- 1000 LTR BUNDED BASE FUEL TANK WITH 3 WAY VALVE
- CT FOR GENSET PARALLELING
- BATTERY CHARGER



- PLASTIC COATED LOCKS AND HANDLES. LOCKABLE CANOPY WITH COMMON SINGLE KEY
- CUMMINS WATER SEPARATOR FILTER
- SUMP OIL VAC PUMP
- OIL PRESSURE SENSOR
- WATER TEMPERATURE SENSOR
- CENTRAL LIFT POINT
- HARDWIRE VIA COPPER BUSBAR
- MICROSWITCH PROTECTION
- MOTORISED MCCB
- RACOR FILTER

ENGINE Ref:- CUMMINS ALTERNATOR Ref:- MECC ALTE

Standby kVA	Prime Power kVA.	Engine Make / Type	Governor	Tank Capacity (litres)	Fuel Consumption (L/H)			Db (A) @ 7m	Size (mm)	Weight (kg)	Control Panel
					50%	75%	100%				
880	800	CUMMINS	Electronic	1000	85	121	161	70	L - 4850 H - 2350 W - 2000	9500	Deep Sea 8610 Loadshare

South East Depot – Europa Park, London Road
Grays, Essex, RM20 4DB
T: 01375 366766 E:power@johnfhunt.co.uk

Midlands Depot – Fairfield Park, Off Fairfield Road,
Halesowen, West Midlands B62 9JL
T: 0121 559 1818 E:power@johnfhunt.co.uk

South West Depot – Bradley Road,
Bristol, BS20 7NZ
T: 0117 901 2199 E:power@johnfhunt.co.uk

North East Depot – Station Lane, Birtley, Gateshead,
Tyne & Wear DH2 1AJ
T: 0191 4111 200 E:power@johnfhunt.co.uk

www.johnfhuntpower.co.uk