



160kVA

Ultra Quiet Fusteq Generator

ENGINE Ref: CUMMINS
ALTERNATOR Ref: LEROY SOMER / MECC ALTE

- Hot dip galvanised sound attenuated enclosure
- Bunded 700 litre base fuel tank complete with 3 way valve
- 4 Base lift points
- 4 Pole circuit breaker with earth leakage Protection with on off switch
- Deep sea 8610 load share control panel
- Plastic coated locks and handles
- Lockable canopy with common single key
- Racor filter
- 50/60 Hz switchable
- Low water level alarm
- Low oil level alarm
- Cummins water separator filter
- Sump oil vac pump
- Battery isolator
- Low oil pressure sensor
- Water temperature sensor
- CT for genset paralleling
- Hardwire via copper busbar
- Microswitch protection
- Motorized MCCB
- Alternator anti condensation heater
- Battery charger
- R731 3 phase regulator

Standby (kVA)	Prime Power (kVA)	Engine Make / Type	Governor	Tank Capacity (Litre)	Fuel Consumption per hour (Litre)			dBA @ 7m	Size (mm)	Wet Weight (kg)	Control Panel
					50%	75%	100%				
165	150	CUMMINS	Electronic	700	22	26.5	40	57	L 3450 W 1110 H 2180	3582	Deep Sea 8610 Loadshare

South East Depot

Europa Park,
London Road,
Grays, Essex,
RM20 4DB
T: 01375 366766

Midlands Depot

Fairfield Park,
Off Fairfield Road,
Halesowen,
West Midlands
B62 9JL
T: 0121 559 1818

South West Depot

Bradley Road,
Bristol
BS20 7NZ
T: 0117 901 2199

Scotland Depot

Nasmyth Square
Livingston
West Lothian
EH54 5GG
T: 01506 353 399

North East Depot

Portobello Trading
Estate
Shadon Way
Chester-Le-Street
DH3 2RN
Tel: 0191 411 1200

Email us: power@johnfhunt.co.uk
johnfhuntpower.co.uk