



# 200kVA

## Ultra Quiet Fusteq Generator

ENGINE Ref: CUMMINS

ALTERNATOR Ref: LEROY SOMER / MECC ALTE

- Hot dip galvanised sound attenuated enclosure
- Bunded 700 litre base fuel tank complete with 3 way valve
- 4 Base lift points
- 4 Pole circuit breaker with earth leakage Protection with on off switch
- Deep sea 8610 load share control panel
- Plastic coated locks and handles
- Lockable canopy with common single key
- Racor filter
- 50/60 Hz switchable
- Low water level alarm
- Low oil level alarm
- Cummins water separator filter
- Sump oil vac pump
- Battery isolator
- Low oil pressure sensor
- Water temperature sensor
- CT for genset paralleling
- Hardwire via copper busbar
- Microswitch protection
- Motorized MCCB
- Alternator anti condensation heater
- Battery charger
- R731 3 phase regulator

Standby (kVA)	Prime Power (kVA)	Engine Make / Type	Governor	Tank Capacity (Litre)	Fuel Consumption per hour (Litre)			dBA @ 7m	Size (mm)	Wet Weight (kg)	Control Panel
					50%	75%	100%				
220	200	CUMMINS	Electronic	700	22	32.5	43.5	56	L 3450 W 1110 H 2180	3982	Deep Sea 8610 Loadshare

### South East Depot

Europa Park,  
London Road,  
Grays, Essex,  
RM20 4DB  
T: 01375 366766

### Midlands Depot

Fairfield Park,  
Off Fairfield Road,  
Halesowen,  
West Midlands  
B62 9JL  
T: 0121 559 1818

### South West Depot

Bradley Road,  
Bristol  
BS20 7NZ  
T: 0117 901 2199

### Scotland Depot

Nasmyth Square  
Livingston  
West Lothian  
EH54 5GG  
T: 01506 353 399

### North East Depot

Portobello Trading  
Estate  
Shadon Way  
Chester-Le-Street  
DH3 2RN  
Tel: 0191 411 1200

power@johnfhunt.co.uk

**johnfhuntpower.co.uk**

2022

