



# 1260kVA

## Silenced Generator

Engine Ref: CUMMINS

ALTERNATOR Ref: LEROY SOMER / MECC ALTE

- Hot dip galvanised sound attenuated enclosure
- Bunded 2000 litre base fuel tank complete With 3 way valve
- 4 Base lift points
- 4 Pole circuit breaker with earth leakage Protection with on off switch
- Deep sea 8610 load share control panel
- Plastic coated locks and handles
- Lockable canopy with common single key
- Racor filter
- 50/60 Hz switchable
- Low water level alarm
- Low oil level alarm
- Cummins water separator filter
- Sump oil vac pump
- Battery isolator
- Low oil pressure sensor
- Water temperature sensor
- CT for genset paralleling
- Hardwire via copper busbar
- Microswitch protection
- Motorized MCCB
- Alternator anti condensation heater
- Battery charger
- R731 3 phase regulator

Standby (kVA)	Prime Power (kVA)	Engine Make Type	Governor	Tank Capacity (Litres)	Fuel Consumption per hour (Litres)			dBA @ 7m	Size (mm)	Wet Weight (kg)	Control Panel
					50%	75%	100%				
1375	1260	CUMMINS	Electronic	2000	112	172	234	62	20' High Cube Container	19500	Deep Sea 8610 Loadshare

### Power Depots:

#### Midlands

Aldridge  
West Midlands  
WS9 8EZ  
Tel: 0121 559 1818

#### South East

Europa Park  
Grays  
RM20 4DB  
Tel: 0137 536 6766

#### South West

Bradley Road  
Bristol  
BS20 7NZ  
Tel: 0117 901 2199

#### West Yorkshire

Flanshaw Way  
Wakefield  
WF2 9PL  
Tel: 0192 497 7077

#### North East

Shadon Way  
Chester-le-Street  
DH3 2RN  
Tel: 0191 411 1200

#### Scotland

Livingston  
West Lothian  
EH54 5GG  
Tel: 01506 353 399

#### John F Hunt Fuels

Tel: 0808 175 1111

